

Wavetable Sample ROM for Music Synthesis

Features

- PCM sample data for General MIDI melodic instrument and percussion sets
- Also includes samples for GS compatible drum kits and special effects sounds
- Compressed data may be used to generate up to 343 sounds (190 instrument sounds, 107 percussion sounds and 46 special effects)
- Low-power operation:
Operating current: 15 mA (max.)
Standby current: 100 μ A (max.)
- Static CMOS operation,
TTL-compatible I/O

General Description


The CS4112 Read Only Memory (ROM), organized 1M x 8bits, contains PCM waveform data used by the CS9233 family of wavetable music synthesizers and associated firmware to provide complete General MIDI (GM) and Roland GS format compliant instrument and sound effect sets.

Proprietary compression and data reduction techniques were used to minimize stored data. When combined with Crystal's Microcode Firmware, high fidelity music and special effects result.

The CS4112 offers a power-down mode controlled by the Chip Enable $\overline{CE}$ input.

ORDERING INFORMATION

CS4112-CS 32-pin SOIC (14x21x3mm)



**GENERAL
MIDI**



Preliminary Product Information

This document contains information for a new product. Crystal Semiconductor reserves the right to modify this product without notice.

DC Electrical Characteristics ($T_A = 0^\circ\text{C}$ to $+70^\circ\text{C}$, $V_{CC} = 5.0\text{V} \pm 10\%$, $\text{GND} = 0\text{V}$)

Parameter	Symbol	Min	Typ	Max	Units
Input LOW Voltage	V_{IL}	-0.5	-	0.8	V
Input HIGH Voltage	V_{IH}	2.2	-	$V_{CC}+0.3$	V
Output LOW Voltage $I_{OL} = 2.1\text{ mA}$	V_{OL}	-	-	0.4	V
Output HIGH Voltage $I_{OH} = -1.0\text{ mA}$	V_{OH}	2.4	-	V_{CC}	V
Input Leakage Current $V_{IN} = 0\text{V}$ to 5.5	$ I_{LI} $	-	-	10	μA
Output Leakage Current $V_{OUT} = 0\text{V}$ to 5.5	$ I_{LO} $	-	-	10	μA
Operating Supply Current	I_{CC}	-	15	40	mA
Standby Supply Current $\text{CE} = V_{IH}$	I_{SB}	-	-	1.0	mA
Power-Down Supply Current $\text{CE} > V_{CC} - 0.2\text{V}$	I_{SB1}	-	-	100	μA

RECOMMENDED OPERATING CONDITIONS ($T_A = 0^\circ\text{C}$ to $+70^\circ\text{C}$)

Parameter	Symbol	Min	Typ	Max	Units
Ambient Operating Temperature	T_A	0	-	+70	$^\circ\text{C}$
Supply Voltage	V_{CC}	+4.5	+5.0	+5.5	V
Supply Ground	GND	0	0	0	V


ABSOLUTE MAXIMUM RATINGS

Parameter	Symbol	Min	Max	Units
Storage Temperature		-65	+125	$^\circ\text{C}$
Supply Voltage to Ground Potential		-0.5	+7.0	V
Output Voltage		-0.5	$V_{CC}+0.5$	V
Input Voltage		-0.5	$V_{CC}+0.5$	V
Power Dissipation		-	1	W

AC CHARACTERISTICS ($T_A = 0^\circ\text{C}$ to $+70^\circ\text{C}$, $V_{CC} = 5.0\text{V} \pm 10\%$, $\text{GND} = 0\text{V}$)

Parameter	Symbol	Min	Typ	Max	Units
Cycle Time	t_{cyc}	120	-	-	ns
Address Access Time (Normal Read) (Note 1)	t_{aa}	-	72	120	ns
Chip Enable Access Time (Note 1)	t_{ace}	-	87	120	ns
Output Enable Access Time (Note 1)	t_{aoe}	-	18	80	ns
Output Hold After Address Change	t_{oh}	10	-	-	ns
Output HIGH Z Delay	t_{hz}	-	-	70	ns
Power down Time (Note 2)	t_{pd}	-	-	100	ns
Power up Time (Note 2)	t_{pu}	0	-	-	ns

Notes: 1. The minimum parameter is sampled and not 100% tested.



FUNCTIONAL OVERVIEW

The CS4112 contains PCM sample data which is processed by the CS9233 (or CS9203) and associated firmware in order to generate high quality melodic instrument, percussion, and special effects sounds. The CS4112's 1 Msample data set includes all of the samples needed to implement a complete General MIDI (GM) compliant and GS compatible synthesizer. A typical connection diagram for the CS4112 with the CS9233 is shown in Figure 1. In this case an optional DRAM memory is also included for downloadable sample data. For more information see the CS9233 Integrated Wavetable Music Synthesizer data sheet and the CS9233 Microcontroller Firmware data sheet.

System Solutions

The CS4112 may be used in system solutions using either the CS9203 Advanced Music Synthesizer or the CS9233 Integrated Wavetable Music Synthesizer.

Crystal Semiconductor provides complete reference design data kits for a variety of system solutions. The reference design kits include functional boards, plus data sheets containing complete schematics, board layouts, Bill of Materials (BOM), technical overviews, and firmware descriptions. Please contact Crystal Semiconductor for information on reference designs employing the CS9233 wavetable synthesizer and CS4112 wavetable sample ROM.




Figure 1. Typical Connections of CS4112 and optional DRAM to the CS9233

Schematic & Layout Review Service


**Confirm Optimum
Schematic & Layout
Before Building Your Board.**

**For Our Free Review Service
Call Applications Engineering.**



Call : (5 1 2) 4 4 5 - 7 2 2 2

PIN DESCRIPTIONS



GND - Power Ground. Pin 16.

The ground pin should be connected to a low impedance ground plane.

VCC - +5V $\pm$ 10%. Pin 32.

The power pin should be connected to a low impedance digital power plane.

WA0-WA19 - Address Input. Pins 12-5, 27, 26, 23, 25, 4, 28-29, 3-2, 30-31, 1.

These input address lines are used to address the stored PCM data.

WD0-WD7 - Output Data. Pins 13-21.

These output data lines provide the data.


CE - Chip Enable. Active low. Pin 22.

This active low input signal is a chip select, and also acts as the Power-down pin.

OE - Output Enable. Active low. Pin 24.

This active low input signal puts the PCM data stored at the address on the specified by WA0-WA19 on the output data lines WD0-WD7.

MECHANICAL DESCRIPTION



pins	MILLIMETERS			INCHES		
	MIN	NOM	MAX	MIN	NOM	MAX
16	9.91	10.16	10.41	0.390	0.400	0.410
20	12.45	12.70	12.95	0.490	0.500	0.510
24	14.99	15.24	15.50	0.590	0.600	0.610
28	17.53	17.78	18.03	0.690	0.700	0.710

DIM	MILLIMETERS			INCHES		
	MIN	NOM	MAX	MIN	NOM	MAX
A	2.41	2.54	2.67	0.095	0.100	0.105
A₁	0.127	-	0.300	0.005	-	0.012
A₂	2.29	2.41	2.54	0.090	0.095	0.100
b	0.33	0.46	0.51	0.013	0.018	0.020
c	0.203	0.280	0.381	0.008	0.011	0.015
D	see table above					
E	10.11	10.41	10.67	0.398	0.410	0.420
E₁	7.42	7.49	7.57	0.292	0.295	0.298
e	1.14	1.27	1.40	0.040	0.050	0.055
L	0.41	-	0.89	0.016	-	0.035
μ	0°	-	8°	0°	-	8°

Note: The inches dimensions were estimated from the millimeter dimensions. For board layout purposes, the millimeter dimensions should be used.

CRYSTAL SOFTWARE LICENSE AGREEMENT

Crystal Semiconductor Corp. CS9233 Firmware releases, sample ROMs, and reference designs contain copyrighted software and wavetable sample data. Under this license agreement Crystal grants to you the right to use one copy of the software and wavetable data ("Licensed Software"), for the purpose of evaluating Crystal Semiconductor Corp. products. You may not:

1. modify, translate, reverse engineer, decompile, disassemble, create derivative works based on the Licensed Software, or copy the Licensed Software; or
2. rent, distribute, lend, or otherwise disclose, transfer or grant any rights in the Licensed Software in any form to any third party, or
3. disclose to any third party, or use for any purpose other than evaluation of the Licensed Software, any information that you learn or derive concerning the Licensed Software as a result of your use or possession of the Licensed Software; or
4. remove any proprietary notices, labels, or marks on or in the original or any copy of the Licensed Software.

THE LICENSED SOFTWARE IS PROVIDED TO YOU "AS IS." CRYSTAL MAKES NO WARRANTY OR REPRESENTATION, EITHER EXPRESS, IMPLIED, STATUTORY, OR OTHERWISE, WITH RESPECT TO THE LICENSED SOFTWARE, INCLUDING ITS QUALITY, PERFORMANCE, MERCHANTABILITY, NON INFRINGEMENT, OR FITNESS FOR A PARTICULAR PURPOSE.

IN NO EVENT SHALL CRYSTAL BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, INCIDENTAL, OR OTHER DAMAGES WHATSOEVER (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR COVER, LOSS OF BUSINESS PROFITS, BUSINESS INTERRUPTION, LOSS OF BUSINESS INFORMATION, OR ANY OTHER PECUNIARY LOSS) ARISING OUT OF THE USE OF OR INABILITY TO USE THE LICENSED SOFTWARE, EVEN IF CRYSTAL HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

TRADEMARKS & COPYRIGHTS

Crystal Clear[™] is a registered trademark of Crystal Semiconductor Corp.

MS DOS[™] and Microsoft[™] are registered trademarks and Windows and Windows Sound System are trademarks of Microsoft Corp.

Sound Blaster[™] Pro is a trademark of Creative Labs, Inc.

AdLib[™] is a registered trademark of AdLib Multimedia, Inc.

The GS[®] logo and SoundCanvas[®] are registered trademarks of Roland Corp. Roland[™], MPU-401[™], and MT-32[™] are trademarks of Roland Corp.

The General MIDI logo is a servicemark of the MIDI Manufacturers Association.

The Fat Seal and The Fat Man are trademarks of George Alistair Sanger and Team Fat, used with permission.

All other brand or product names mentioned are trademarks or registered trademarks of their respective holders.

• Notes •